

## POCKET SIZE DIGITAL MULTIMETER

# KPS-MT10



- Pocket digital multimeter
- 4000 accounts
- Measurement of DC / AC voltage, DC / AC current, resistance, capacity and frequency
- Continuity warning and diode test
- Retention of readings
- Automatic scale
- Backlit screen
- Auto power off and low battery indicator
- CAT.II 600V / CAT. III 300V according to EN 61010



# KPS-MT10

## POCKET SIZE DIGITAL MULTIMETER

General	
Power Supply	2×1.5V 357A(LR44) Batteries
Product Size	120mm×70mm×18mm
Product Weight	110g
Certificate	CE/ETL/RoHS
Safety Rating	CAT III 300V/CAT II 600V

Specs	
Display Counts	4000
Auto Power Off	✓
Auto Ranging	✓
Diode	1.5V
Continuity Buzzer	✓
Data Hold	✓
Low Battery Indicator	✓



# KPS-MT10

## POCKET SIZE DIGITAL MULTIMETER

Specs	Range	Resolution	Accuracy
DC Voltage	400mV/4V/40V/400V	0.1mV/1mV/10mV/100mV	$\pm(0.5\%+3)$
	600V	1V	$\pm(0.8\%+3)$
AC Voltage	4V/40V/400V	1mV/10mV/100mV	$\pm(0.8\%+4)$
	600V	1V	$\pm(1.0\%+4)$
DC Current	40mA/400mA	0.01mA/0.1mA	$\pm(2.0\%+3)$
AC Current	40mA/400mA	0.01mA/0.1mA	$\pm(3.0\%+4)$
Resistance	400 $\Omega$ /4k $\Omega$ /40k $\Omega$	0.1 $\Omega$ /1 $\Omega$ /10 $\Omega$	$\pm(1.0\%+3)$
	400k $\Omega$ /4M $\Omega$	0.1k $\Omega$ /1k $\Omega$	
	40M $\Omega$	10k $\Omega$	$\pm(2.0\%+4)$
Capacitance	4nF	1pF	$\pm(5.0\%+10)$
	40nF	10pF	$\pm(4.0\%+5)$
	400nF/4 $\mu$ F/40 $\mu$ F/100 $\mu$ F	0.1nF/1nF/10nF/0.1 $\mu$ F	$\pm(3.0\%+3)$
Frequency	10Hz/100Hz/1kHz/ 10kHz/100kHz	0.01Hz/0.1Hz/1Hz/ 10Hz/0.1kHz	$\pm(0.5\%+3)$

### Product Code Information

SKU	KPSMT10CBINT
EAN code	8435394710235
UPC code	810053673546
Pcs/export carton	40