




# TRMS VOLTAGE AND CURRENT TESTER

## TP5000HY



- Dual visualisation via LED indicator scale and LCD display (10000 counts)
- AC/DC voltage up to 1000V
- Current measurement up to 200 Aac
- Peak current measurement
- True RMS in Vac and Aac
- Phase rotation test
- Pole search function
- Data hold (HOLD)
- Battery-free voltage measurement
- Removable test probes
- Built-in torch
- IP65 PROTECTION
- Compliance with IEC/EN 61243-3:2014



**TRMS VOLTAGE AND CURRENT TESTER**

General	
TRMS	✓
LCD	10000 counts
Vac/dc LEDs scale	✓
IP	IP65
Sampling rate	3 veces/seg
Low Battery Indicator	✓
Auto Power Off	✓
Max diameter of cable	16mm
Jaw size	39mm
Batteries	AAA x2(R03, LR03, 24D, 24A)
Dimensions	57mm x 220mm x 35mm
Weight	200 g
Standards	IEC/EN 61243-3:2014
Safety rating	CAT IV 600V, CAT III 1000V
Accesories included	Teas lead and pouch

# TP5000HY

## TRMS VOLTAGE AND CURRENT TESTER

Specs	
AC Current	200,0 A
AC Voltage	with Batteries: 6,0V-1000V Without Batteries: 45V-1000V
DC Voltage	With Batteries: 7,0V-1000V without Batteries: 35V-1000V
Resistance	50k $\Omega$
Continuity Buzzer	<1.8K $\Omega$ , 2.7KHz tono buzzer
Phases sequence	Sensibility (90V-1000V) Frequency range:45-65 Hz
Single phase test	Sensibility (90V-1000V) Frequency range:45-65 Hz

Product Code Information	
SKU	KPSTP5000HYCBINT
EAN code	8435394784748
UPC code	810053676653
pcs/export carton	20